

Relay Module

S312N-8

This single PCB contains 8 of our transistor driven DPCO. Interface relay modules. All modules operate independently but have power pre connected on the PCB for convenience. The modules accept a variety of input conditions (Voltage, Logic, Closed Circuit and Open Circuit) for interfacing various signals via voltage free DPCO contacts.

Specification	S312N-8
Led Current	N/A
Switch Contacts	DPCO contacts rated at 2A
Visual Indication	8 x Red located on inside of box
Integral Sounder Level	N/A
Power Supply	Integral 230vac to 12vdc 5A
Supply Input Current	480 mA max
Tamper	N/A
Material	PCB Module
Dimensions	155 x 110 x 14 mm
Weight	0.2kg
IP Rating	N/A
Approvals	UKCA and CE marked, ROHS compliant

Benefits and Features

- 8 x Relay on a single board
- Requires 12vdc supply at 240mA
- DPCO contacts Rated at 2amp
- Intended for internal use only
- Four mounting holes provided for mounting on self adhesive pillars (supplied)
- Relay has screw terminals for easy connection
- Manufactured in the UK

