

## S370

The S370 allows up to 16 normally open inputs to trigger 16 normally open outputs using a single network cable up to 500 meters.

The outputs all follow the inputs, e.g. if a button across IN1 is pressed then OUT1 would close whilst the button is pressed.

Outputs 16 N/O relays rated 500mA up to 60V with max power dissipation of 500mW.

Requires a separate 12 vdc PSU Max 500mA, connected to the input pcb. **Please note: If cable length is greater than 100m then a separate 12vdc PSU is also required at the output PCB.**

To trigger an input, short INx A with INx B – this will cause a short from OUTx A to OUTx B

