

## Aidalarm – Wireless Disabled Toilet Alarm

## A600WKITM, A600WKITB, A600WKIT12

This wireless kit meets the requirements for emergency signalling systems for disabled persons. It is fully compliant with BS8300 and the Disability Discrimination Act. Everything is provided in the kit to deliver an effective, fully compliant, simple to install and simple to use system. The controller is available in battery(A600WB), 12V (A600W12) or mains powered (A600WM).

All remote devices used are also battery powered, avoiding conflict with Part P building regulations. If required the 12V and mains controllers can use a combination of wireless and wired remote devices, batteries are supplied in all units.

## Benefits and Features

- DDA & BS8300 Compliant
- Wireless Technology 433MHz
- Controller & overdoor indicator with audio and visual indication
- Mains, 12V or Battery powered kits available
- Battery status of ancillary devices is monitored by controller
- Low Battery Warning
- Backup batteries on A600WM
- Audible & Visual Signalling to remote point
- Optional Dado Panic Strip or Call Button
- Eight devices can be connected to one controller
- All required batteries supplied
- Manufactured in the UK

## A600WKITB (Battery), A600WKIT12 (12 Volts)

## A600WKITM (Mains) Includes

- 1 x A600WB, A600W12 or A600WM Wireless controller
- 1 x S1600R-W Wireless Pull cord with re-assurance LED
- 1 x LAB35107 Wireless Pull cord instruction label with braille text
- 1 x S1778W Wireless Overdoor light and sounder
- 1 x S1708W Wireless Reset button, re-assurance LED and braille text

## How the Aidalarm Works

1. The Aidalarm controller should be sited where staff are located who can respond to an emergency call.
2. Ceiling pull cord, optional Dado panic strip or call buttons are situated in toilet or other area where assistance may be required.
3. Pulling the cord or pressing the panic strip/call button generates an audible/visual alarm at both the WC area and at the control panel. An LED will flash on the pull cord giving the caller reassurance that the call has been placed, this LED will extinguish when it receives acknowledgement from the controller.
4. The call can be silenced by pressing the button on the front of the control panel.
5. The audible indicators at the WC will bleep to re-assure the caller.
6. Should the cord be pulled again while in the silenced state, the system will call again.
7. Non-attendance will cause the panel to bleep every 3 minutes as a warning.
8. The system can only be reset by the Press to Reset button located at or near the point of call.



If using Dado Panic Strip, a S1705W Call button will also be required.

**Please Note:** There may be slight delay on the battery powered version due to power saving measures.

