

GEO 14AS

Single line alphanumeric pager



features

- Large 14 Character Scrolling Display
- Frequency Programmable
- VHF & UHF Versions

Clear and simple

The frequency programmable pager with a large one-line text display. If the message is longer than 14 characters, an auto scroll feature can be used. The scroll speed can be set by the user.

GEO 14AS

Single line
alphanumeric pager

Specification

Display:	Side read, 14 character, backlit with icons
Addresses:	4 addresses (selectable)
Messages:	16 messages max., 840 characters max, message length 120 char. max
Size:	68 (L) x 46 (W) x 21 (D) mm w/o holster
Weight:	46g (without battery)
Frequency ranges:	VHF 151-159 MHz, UHF 446-454, 454-462, 462-470 MHz
Signalling protocol:	POCSAG
Data transmit rate:	512, 1200 or 2400 baud
Sensitivity:	5 μ V/m @ 512 baud, 7 μ V/m @ 1200 baud
Beeper output:	Better than 75 db @ 10cm
Power:	Single AAA (LR03) battery



Main features

- **Scrolling Display:** If the message is longer than 14 characters, an auto scroll feature can be used to read the remaining message. The scroll speed can be set by the user.
- **Synthesized:** The operating frequency can be programmed within the specified range.
- **Urgent Call:** Distinct tone + vibrate mode ideal for emergency services (Fire, Police, Hospitals). Can be pre-programmed to respond to a specific address and call type.
- **Hand Programmable:** The pager addresses and operating frequency can be altered using the buttons on the pager. These features can be individually enabled or inhibited when the pager is first programmed.
- **Selectable Functions:** Both the Repeat Message and Reminder Alert functions can be enabled or inhibited when the pager is first programmed.
- **Multiple Alert Modes:** Tone (4 beep styles)
Melody
Vibrate
"Urgent" Tone + Vibrate

Other features

- All or Single Message Delete
- Real Time Clock
- Alarm Clock Function
- Unread Message Indicator & reminder
- Repeat Message Indicator
- Low Battery Reminder
- In/Out of Range Indicator
- Selectable Backlight



Scope Communications UK Ltd
Quantum House
Steamer Quay
Totnes, Devon, TQ9 5AL
England

Tel: +44 (0)1803 860700
Fax: +44 (0)1803 863716
Website: www.scope-uk.com
Email: sales@scope-uk.com