

Wireless Aidalarm Press to Reset with LED

S1708W

Wireless wall mounting Press to Reset button with Braille text plus 2 yellow LEDs for caller reassurance. Enclosed in white ABS plastic, complete with a single gang surface mounting box.

Battery status is monitored by the control panel. When the battery requires replacing, the control panel will indicate a fault. When fault is indicated replace all batteries within the system. The system should be tested monthly and we recommend that all batteries are replaced every twelve Months.

This wireless unit is specifically designed for use with our wireless Aidalarm Disabled Toilet Alarm systems.

Specification	S1708W
Led Current	N/A
Sounder Current	N/A
Switch Contacts	N/A
Battery Type	CR123 Type Lithium
Visual Indication	2 x High brightness yellow LED's
Integral Sounder Level	N/A
Tamper	N/A
Material	White ABS
Dimensions	87 x 87 x 36mm
Weight	0.14kg
IP Rating	IP44 - To maintain the IP rating a suitable sealant or gasket for the rear of the plate is required
Approvals	UKCA and CE marked, ROHS compliant

Benefits and Features

- Wireless Technology 433MHz
- Battery powered
- Battery status monitored by controller
- Back box supplied for surface mount
- Mark resistant decal
- Tactile button
- Two high brightness yellow LEDs



Dimensions (mm)

